

Amendments to the Claims

1. (currently amended) A compass system comprising:
a 2-axis magnetic sensor ~~at least one magnetic sensor~~;
a tilt sensor;
a memory;
a processor;
at least one value for the Earth's magnetic field strength stored in the memory; and
a set of instructions stored in the memory and executable by the processor to calculate a magnetic field component, Z, that is orthogonal to measurement axes associated with the 2-axis magnetic sensor ~~measurement axes~~, using inputs from the 2-axis magnetic sensor and using the at least one stored value for the Earth's magnetic field strength.
2. (canceled)
3. (currently amended) The system of claim 1 ~~2~~, wherein the ~~orthogonal~~ field component Z is calculated as $Z = \sqrt{H^2 - X^2 - Y^2}$ where H is the at least one stored value, X is a first measurement from the 2-axis magnetic sensor and Y is a second measurement from the 2-axis magnetic sensor that is orthogonal to X.

4. (currently amended) The system of claim 3, further comprising ~~calculating local horizontal components of the Earth's magnetic field using the calculated value of Z and inputs from the tilt sensor~~ a set of instructions in memory and executable by the processor to calculate local horizontal components of the Earth's magnetic field X_{comp} and Y_{comp} using the calculated value of Z and inputs from the tilt sensor.

5. (original) The system of claim 4, wherein the tilt sensor is a 2-axis tilt sensor that measures pitch (Φ) and roll (θ) angles and wherein the local horizontal components X_{comp} and Y_{comp} are mutually orthogonal and are calculated using the equations;

$$X_{comp} = X \cos \Phi + Y \sin^2 \Phi - Z \cos \theta \sin \Phi \quad \text{and}$$

$$Y_{comp} = Y \cos \theta + Z \sin \theta.$$

6. (original) The system of claim 5, wherein a compensated heading is calculated using the equation

$$\text{Heading} = \text{arcTan}(Y_{comp} / X_{comp}).$$

7. (currently amended) A method of compensating for tilt in an electronic compass having a 2-axis magnetic sensor and a tilt sensor, the method comprising:

storing at least one value for the Earth's magnetic field strength;

measuring the Earth's magnetic field strength with the 2-axis magnetic sensor; and

calculating a magnetic field component, Z, that is orthogonal to the measurement axes ~~associated with the 2-axis magnetic sensor measurement axes,~~ using the measured field

strengths from the 2-axis magnetic sensor and using the at least one stored value for the Earth's magnetic field strength.

8. (original) The method of claim 7, further comprising:

calculating the orthogonal field component Z using the equation $Z = \sqrt{H^2 - X^2 - Y^2}$ where H is the at least one stored value, X is a first measurement from the 2-axis magnetic sensor and Y is a second measurement from the 2-axis magnetic sensor that is orthogonal to X .

9. (original) The method of claim 8, further comprising:

calculating local horizontal components X_{comp} and Y_{comp} of the Earth's magnetic field using the calculated value of Z and inputs from the tilt sensor, wherein the tilt sensor is a 2-axis tilt sensor that measures pitch (Φ) and roll (θ) angles and wherein the local horizontal components X_{comp} and Y_{comp} are mutually orthogonal and are calculated using the equations;

$$X_{comp} = X \cos \Phi + Y \sin^2 \Phi - Z \cos \theta \sin \Phi \quad \text{and}$$

$$Y_{comp} = Y \cos \theta + Z \sin \theta.$$

10. (original) A method of compensating for tilt in an electronic compass having a 2-axis magnetic sensor and a tilt sensor, the method comprising:

storing at least one value for the Earth's magnetic field strength;

measuring the Earth's magnetic field strength with the 2-axis magnetic sensor;

calculating a magnetic field component, Z , that is orthogonal to the 2-axis magnetic sensor measurement axes using the measured field strengths from the 2-axis magnetic sensor and using the at least one stored value for the Earth's magnetic field strength, wherein the orthogonal field component Z is calculated using the equation $Z = \sqrt{H^2 - X^2 - Y^2}$ where H is the at least one stored value, X is a first measurement from the 2-axis magnetic sensor and Y is a second measurement from the 2-axis magnetic sensor that is orthogonal to X ;

calculating local horizontal components X_{comp} and Y_{comp} of the Earth's magnetic field using the calculated value of Z and inputs from the tilt sensor, wherein the tilt sensor is a 2-axis tilt sensor that measures pitch (Φ) and roll (θ) angles and wherein the local horizontal components X_{comp} and Y_{comp} are mutually orthogonal and are calculated using the equations;

$$X_{comp} = X \cos \Phi + Y \sin^2 \Phi - Z \cos \theta \sin \Phi \text{ and}$$

$$Y_{comp} = Y \cos \theta + Z \sin \theta; \text{ and}$$

calculating a compensated heading using the equation

$$\text{Heading} = \arctan(Y_{comp} / X_{comp}).$$